

MULTI-SENSOR DETECTOR

MIX-4020 / MIX-4020-ISO



MIX-4020 / MIX-4020-ISO

Description

The MIX-4020/MIX-4020-ISO multi-criteria detector is a hardwired sensor that continuously monitors the environment to provide early warning of a fire condition and communicates with the panel using a fully digital protocol.

The MIX-4020/MIX-4020-ISO provides a higher level of nuisance alarm rejection as compared with single-criteria sensors leveraging both smoke and heat sensing elements.

The MIX-4020/MIX-4020-ISO works with an Secutron compatible control panel supporting high rates of information exchange with reliable and secure bi-directional communication.

The detector is addressed and programmed using the MIX-4090 hand-held device. Addresses can be selected from a range of 1 -240.

This detector ships with a dust cover to protect the device during installation and prior to commissioning.

Two tri-color LEDs on the device provide 360 degrees of status visibility.

A remote LED indicator can be wired directly to the sensor.

Features

- Any combination of MIX-4000 series devices up to 240 can be connected on a single SLC.
- Different LED colors for Alarms and Troubles.
- Detection of smoke using advanced software algorithms using complementary thermal sensor.
- Advanced Protection against nuisance alarms caused by dust, insects, or other debris.
- Multiple sensitivity settings.
- Compatible with the full series of MIX-4000 input and control modules.
- The device can be secured by a unique Anti-Tamper feature.
- The Address is set with the hand-held device programmer (MIX-4090)
- MODEL OPTION - Built-In short-circuit isolator (MIX-4020-ISO)

Benefits

- Open style mounting bases offer easy wiring and low pressure locking.
- 4" or 6" base options available.
- Remote output can be controlled by the panel.
- MIX-4020-ISO is equipped with a bi-directional short-circuit isolator to protect against wiring faults and loop failure.
- Low standby current.
- Base has detachable tab for labeling device address.
- Leverages interrupts to quickly report alarm conditions to fire alarm control panels.
- Magnet test option helps with commissioning and maintenance.



CATALOG NUMBER 9502S

Technical Specifications

Normal Operating Voltage	15 to 30VDC
Maximum Alarm Current	3.2mA (LED on)
Standby Current	160µA
Temperature Range	32°F to 100°F (0°C to 37.8°C)
Humidity	10% to 93% Non-condensing
Wiring range on terminals	22 to 12 AWG
Diameter	4.25"
Height	1.75"

Detector LED colors	Description
RED (Steady on)	ALARM condition
GREEN (Flash)	NORMAL condition
AMBER (Steady on)	FAULT condition

Heat Detection Settings
135°F (57°C)
135°F with rate of rise as per UL268

Sensitivity Level	Typical	Note
LEVEL 1	1.75%/FEET	Most Sensitive level
LEVEL 2	2.25%/FEET	Sensitivity level
LEVEL 3	2.75%/FEET	Sensitivity level
LEVEL 4	3.25%/FEET	Least Sensitive Level

Ordering Information

Model	Description
MIX-4010	Photoelectric Smoke Detector (Non-Isolated)
MIX-4010-ISO	Photoelectric Smoke Detector (with short-circuit isolator)
MIX-4020	Multi-Criteria/Multi-Sensor (Non-Isolated)
MIX-4020-ISO	Multi-Criteria/Multi-Sensor (with built-in short circuit isolator)
MIX-4030	Heat Detector (Non-Isolated)
MIX-4030-ISO	Heat Detector (with built-in short circuit isolator)
MIX-4090	MIX-4000 Series Addressable Device Programmer
MIX-4001	6" Detector Base
MIX-4002	4" Detector Base

CATALOG NUMBER 9502S

NOT TO BE USED FOR INSTALLATION PURPOSES.

Mircor reserves the right to make changes at any time without notice in prices, colours, materials, components, equipment, specifications and models and also to discontinue models.