



Description

The F-LHY5Y is a wall mount speaker built-in 70v/100v transformer. The 70v/100v transformer technique reduces line losses on longer distance and allows easy parallel connection of multiple loudspeakers.

The built-in 4"+1.5" two ways speaker driver is designed of wide frequency response 75-18kHz, the multiple power taps 20W-15W-7.5W are helpful for different applications varies from room size and ambient noise surroundings.

The metal grille, ABS enclosure and stainless mounting bracket are of black color. Easy and secure wall mount installation through the supplied mounting bracket.

It is ideal choice for industrial and commercial applications in hotel, school, office and factory where background music and paging is needed.

Specification

Product Model	F-LHY5Y
Impedance	8 ohms
Bass speaker	5.25" (131mm)
High-pitched speaker	0.5"(13mm)
Sensitivity	88dB
Frequency Range	80-18KHz
Power Taps @100V	30W, 20W
Mounting	Flush-mount dog ears
Frequency Range	80HZ-18KHZ
Finish	
Dimensions	175*156*80mm
Dimensions	175*156*80mm